

SIEMENS TYPE	BREAKERS INSTALLED ARE SIEMENS TYPE	CURRENT RATING IN RMS SYMMETRICAL AMPS, 120/240 V~ IS
NONE USED of EQ8693, EQ8695 or QP	QP, QPH, HQP, QT, QG, QAF, QAFH, QPF, QPHE, QE, QEH, QNR, QNRH, HQNR	10,000
EQ8693, EQ8695 or QPH	QP, QPH, HQP, QT, QAF, QAFH, QPF, QPHE, QE, QEH, QNR, QNRH, HQNR	22,000
NONE USED of EQ8693, EQ8695	QPH, QAFH, QPHE, QEH, QNRH	
NONE USED	QP, QPH, HQP, HQNR	42,000
NONE USED of EQ8693, EQ8695 or HQP	QP, QPH, HQP, QT, QAF, QAFH, QPF, QPHE, QE, QEH, QNR, QNRH, HQNR	65,000
NONE USED	HQP, HQNR	


ADDITION OF FIELD INSTALLED MAIN BREAKER KIT OR A MAIN ACCESSORY TABLE FOR CATALOG NUMBERS OF APPROPRIATE KITS.

## USE COPPER OR ALUMINUM 60°/75°C WIRE

SEE BREAKER MARKINGS FOR WIRE SIZE AND TORQUE REQUIREMENTS.

TERMINALS	WIRE	TORQUE
A, B	300 kcmil - 4 AWG	275 LB-INS
N	4/0 - 4 AWG CU; 300kcmil - 4 AWG AL	275 LB-INS
MAIN BREAKER	3/0 AWG CU; 250 kcmil AL MAX.	See Breaker
G	2/0-4 AWG	110 LB-INS
NEUTRAL/GROUND BARS (USE TYPE EC1GB or EC2GB GND BAR KIT ACCESSORY)	10-14 CU/10-12 AL	20 LB-INS
	8 AWG	25 LB-INS
	6-4 AWG	35 LB-INS
GROUND CONDUCTORS ONLY	(2) or (3) 14 AWG	20 LB-INS
	(2) 12-10 AWG	20 LB-INS
ECLK1-2 NEUTRAL LUG KIT	2/0-2 AWG	45 LB-INS
ECLK2 NEUTRAL LUG KIT	2/0-4 AWG	135 LB-INS
ECLK3 NEUTRAL LUG KIT	300 kcmil - 1 AWG	340 LB-INS
MAIN LUG/MAIN BRKR TO BUS CONNECTION (1/4-20 NUT)		45 LB-INS
BONDING SCREW		45 LB-INS

SUB-FEED LUGS




G  
N

EQPT

EQPT

SUB-FEED LUGS



G  
N

EQPT